

iclever

## 折り畳みワイヤレスキーボード

IC-BK06lite

取扱説明書

www.iclever.co.jp

-1-


パッケージ内容

- 1xワイヤレスキーボード
- 1xホルダー
- 1xマイクロUSBケーブル
- 1x取扱説明書
- 1x保証カード

仕様

Bluetoothバージョン	Bluetooth 5.1
折り畳みサイズ	313.4 x 92.8 x 7.5mm / 12.34 x 3.65 x 0.3 in
受信距離	< 10 m / 32.8 ft
リチウム電池容量	110 mAh
充電時間	< 2 時間
連続使用時間	40 時間
待機時間	30 日
表面材質	ABS
裏面材質	PU

インジケータ



① 低電力モード: バッテリー残量が少なくなると赤色で点滅します。充電インジケータ: 赤色で点灯します。フル充電: 満充電になると消灯します。

-2-

② パワーオン/オフ: キーボードを開いて、電源スイッチをオンにします。電源インジケータが3秒ほど緑色で点灯した後消灯します。ペアリング: ネットボタンを押すとペアリングモードに入ります。ペアリングモード: 青色で点滅します。ペアリング完了: 自動的に消灯します。

③ マイクロUSB充電ポート: 充電用

注: 当キーボードはキャップロックインジケータが付いておりませんが、キャップロックキーで大文字・小文字の切り替えはできます。

操作手順

ペアリング手順

一台目のデバイスのペアリング

ステップ1. キーボードを開いて、電源スイッチをオンにします。ステップ2. 「Fn」+「Q」キーを押すとチャンネル1に入り、状態インジケータが赤く青色で点滅します。ステップ3. 「Connect」ボタンを押すと、状態インジケータがゆっくり青色で点滅し、ペアリングモードに入ります。デバイスのBluetooth機能をオンにして、使用可能なデバイスを検索します。ステップ4. 「iClever IC-BK06 Lite Keyboard」という名のBluetoothキーボードをクリックして接続します。ステップ5. 接続されると、状態インジケータが消灯します。

二台目デバイスとペアリング

ステップ1. 「Fn」+「W」キーを押すとチャンネル2に入り、状態インジケータが赤く青色で点滅します。ステップ2. 「Connect」ボタンを押すと、状態インジケータがゆっくり青色で点滅し、ペアリングモードに入ります。ステップ3. 画面上のデバイス名から「iClever IC-BK06 Lite Keyboard」をクリックして接続します。ペアリングされた後、状態インジケータが消灯します。

-3-

三台目デバイスとペアリング

ステップ1. 「Fn」+「E」を押すとチャンネル3に入り、状態インジケータが赤く青色で点滅します。ステップ2. 「Connect」ボタンを押すと、状態インジケータがゆっくり青色で点滅し、ペアリングモードに入ります。ステップ3. 画面上のデバイス名から「iClever IC-BK06 Lite Keyboard」をクリックして接続します。ペアリングされた後、状態インジケータが消灯します。

b. 接続された三つのデバイスを切り替えるには? 「Fn」+「Q」/「W」/「E」を同時に押し切り替えます

c. 接続されているチャンネルを再ペアリングするにはどうしたら良いですか? チャンネル1 (またはチャンネル2または3) をデバイス1とすでに接続して、ほかのデバイスをチャンネル1と接続したい場合、次の手順で操作してください。ステップ1. 「Fn」+「Q」キーを押すとチャンネル1に入ります。ステップ2. 「Connect」ボタンを押すと、状態インジケータが青色で点滅し、ペアリングモードに入ります。デバイスのBluetooth機能をオンにして、使用可能なデバイスを検索します。ステップ3. 「iClever IC-BK06 Lite Keyboard」という名のBluetoothキーボードをクリックして接続します。ステップ4. 接続されると、状態インジケータが消灯します。

ご注意:

- 再接続機能: キーボードの電源をオンにすると、最後に使用したデバイスと自動的に接続します。(接続デバイスのBluetooth機能をオンにしてください)
- ペアリングに失敗した場合は、デバイスからペアリング履歴を削除し、上記の手順を再度試してみてください。

-4-

キーボード機能

\*AndroidまたはiOSデバイスのショートカットキーを有効にするには、F1~F12キーを押すと有効に出来ます。  
\*Windowsデバイスで、ショートカットキーを有効にするには、Fn+Shift+F1-F12キーを押すと有効に出来ます。

キーアイコン	Androidシステム	iOSシステム	Windowsシステム (Fn)	Windowsシステム (Fn)+Shift
	N/A	N/A	Esc	N/A
	ホーム	ホーム	F1	ウェブブラウザ
	ブライトネス ダウン	ブライトネス ダウン	F2	ブライトネス ダウン
	ブライトネス アップ	ブライトネス アップ	F3	ブライトネス アップ
	音量下	音量下	F4	音量下
	再生/一時停止	再生/一時停止	F5	再生/一時停止
	消音	消音	F6	消音
	サイレント	サイレント	F7	サイレント
	ボリュームダウン	ボリュームダウン	F8	ボリュームダウン
	ボリュームアップ	ボリュームアップ	F9	ボリュームアップ
	バッテリー残量確認	バッテリー残量確認	F10	バッテリー残量確認
	スクリーンショット	スクリーンショット	F11	N/A
	ロックスクリーン	ロックスクリーン	F12	N/A
	N/A	キーボード表示	N/A	N/A
	戻る	N/A	N/A	N/A
	N/A	N/A	無変換	N/A
	N/A	N/A	変換	N/A
	N/A	N/A	変換	N/A

付属ホルダー

スマートフォンとタブレット両方使える便利なホルダー。

-5-

ご注意: デバイスとペアリングした後、FnとA/S/Dキー (iOSはA, AndroidはS, WindowsはD) を押して、オペレーションシステムを選んでください。その作業をしない、一部のファンクションキーが使用出来なくなります。「Fn+A」→ iOS 「Fn+S」→ Android 「Fn+D」→ Windows

Windows10とAndroidデバイスでは、日本語ローマ字入力のスータスに以下の文字入力方法

Shift+	#	Shift+	&	Shift+	/
Shift+	(	Shift+	)	Shift+	=
Shift+	^	Shift+	~	Shift+	@
Shift+	+	Shift+	[	Shift+	{
Shift+	]	Shift+	;	Shift+	*

ご注意: Windows10システムの場合、日本語がな入力状態で、キーを押して「む」が入力でき、キーを押して「る」が入力できます。

付属ホルダー

スマートフォンとタブレット両方使える便利なホルダー。

-6-

言語切り替え

iOS 8 or below: Cmd + Space  
iOS 9 or above: Ctrl + Space  
Samsung Android: Shift + Space  
Google Android: Ctrl + Space  
Windows: Cmd + Space / Ctrl + Shift

重要事項—入力言語設定

本製品は多国言語対応のため、ご使用前に必ず日本語設定してください。以下のような手順に従って操作してください。

- iOSデバイスの場合  
設定>一般>キーボード>新しいキーボードを追加>日本語を選択
- Samsung Androidデバイスの場合  
設定>コントロール>言語と文字入力>Samsungキーボード>入力言語を選択>日本語を選択
- Androidデバイスの場合  
設定>言語と文字入力>物理キーボード>キーボードレイアウト設定>日本語を選択
- Windowsデバイスの場合  
コントロールパネル>時間・言語・地域>日本語を選択

対応システム

- iOS 6.0以後
- Mac OS X v10.6 to Mac OS X v10.12以後
- Windows XP / Vista / 7 / 8 / 10
- Android 3.0 and above with Bluetooth HID profile (スタートフォンやタブレット)
- 本製品はSamsung Smart TV (UE37ES5500, UE55KU6400U, UE48JU6400), Mac mini and Nokia Sマホには対応できませんので、ご了承ください。

省エネモード

30分間操作しない場合、キーボードが自動的にスリープモードに入ります。再起動するには、任意のキーを押して、3秒ほどお待ちください。

-7-

充電

- 付属されるUSB充電ケーブルを使って充電してください。ケーブルの一端をUSBチャージャーと接続し、もう一端をキーボードに接続してください。(USBチャージャーは別売りです)。
- 充電中電源インジケータが赤色で点灯します。充電が完了まで約2時間かかります (入力: DC 5V/500mA)

FAQ

デバイスと接続できない

以下のような手順に従って操作してください。

- Bluetooth機能がオンになっていることを確認してください。
- デバイスのBluetooth接続記録を削除してください。
- Turn off the Bluetooth on your devices and turn it again
- デバイスとキーボードBK06liteの距離をできる限り近づけてください。
- キーボードとデバイスをフル充電してください。
- キーボードとデバイスを再起動してください。

注: Bluetoothアダプタを介してキーボードを接続している場合、互換性の問題により部分のデータがキーボードと接続できない可能性があります。

日本語入力モードで、入力と出力の句読点が異なる IC-BK06liteキーボードは日本語 (JIS) ではなく、英語 (US) 配列です。入力と出力の句読点が異なります。英語 (US) 入力モードに切り替える時、入力と出力の句読点が一致します。

一部のファンクションキーが使えません

ファンクションキーを使用する前に、上記の「キーボード機能」をお読みください。対応するオペレーションシステムに切り替えられるかどうかを確認してください。(「Fn」+「A」/「S」/「D」キーを押してiOS/Android / Windowsシステムに切り替えます)

-8-

iclever

## Foldable Wireless Keyboard

IC-BK06lite

User Manual

www.iClever.co.jp

-1-


Package Contents

- 1 x Wireless Keyboard
- 1 x Holder
- 1 x Micro USB Cable
- 1 x User Manual
- 1 x Warranty Card

Specifications

Bluetooth version	Bluetooth 5.1
Dimensions	313.4 x 92.8 x 7.5mm / 12.34 x 3.65 x 0.3 in
Operating Range	< 10 m / 32.8 ft
Lithium Battery Capacity	110 mAh
Charge time	< 2 hours
Uninterrupted Work Time	40 hours
Stand-by time	30 days
Front side of keyboard	ABS
Back side of keyboard	PU

Indicator Lights Description



① Low Battery status: flashing in red color reminding to charge. Charging status: stay in red color when charging, and it will be off after fully charged.

-2-

② Power on/off: it turn to be blue for 3s when slide the button to right. Pairing: Press "Connect" button to enter pairing mode. Pairing status: it will flash blue in pairing mode. Successfully Paired: automatically turns off.

③ Micro USB Charging Port: Only for charging.

Note: For Android Users, the Caps lock indicator may not be on but it work as normal.

Operation Instruction

a. How to pair with wireless devices? Pairing with the 1st device

Step 1. On the keyboard, slide the power button to on.

Step 2. Press "Fn"+"Q" keys to enter channel 1, the status indicator will flash blue quickly.

Step 3. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 4. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it.

Step 5. The status indicator will be off after successfully paired.

Pairing with the 2nd device

Step 1. Press "Fn"+"W" keys to enter channel 2, the status indicator will flash blue quickly.

Step 2. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 3. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it. The status indicator will be off after successfully paired.

Pairing with the 3rd device

Step 1. Press "Fn"+"E" keys to enter channel 3, the status indicator will flash blue quickly.

Step 2. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 3. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it. The status indicator will be off after successfully paired.

b. How to switch among 3 devices that have already been connected? Press "Fn" and "Q"/"W"/"E" keys to switch among connected devices.

c. How to re-pair a channel that has already been connected? If you already connect channel 1 (or channel 2 or 3) with device 1, and you want to use another device to connect channel 1 (or channel 2 or 3), please do as following.

Step 1. Press "Fn"+"Q" keys to enter channel 1, the status indicator will flash blue quickly.

Step 2. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 3. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it. The status indicator will be off after successfully paired.

Notes.

- Auto re-connect function. when you turn on the keyboard, it will connect with the last-used device automatically.
- If connection fails, delete all the pairing record from your device, and follow the above instructions again.

-3-

Pairing with the 3rd device

Step 1. Press "Fn"+"E" keys to enter channel 3, the status indicator will flash blue quickly.

Step 2. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 3. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it. The status indicator will be off after successfully paired.

b. How to switch among 3 devices that have already been connected? Press "Fn" and "Q"/"W"/"E" keys to switch among connected devices.

c. How to re-pair a channel that has already been connected? If you already connect channel 1 (or channel 2 or 3) with device 1, and you want to use another device to connect channel 1 (or channel 2 or 3), please do as following.

Step 1. Press "Fn"+"Q" keys to enter channel 1, the status indicator will flash blue quickly.

Step 2. Press "Connect" key to enter pairing mode; the status indicator will flash blue slowly.

Step 3. Find the Bluetooth name "iClever IC-BK06 lite Keyboard" and click to connect it. The status indicator will be off after successfully paired.

Notes.

- Auto re-connect function. when you turn on the keyboard, it will connect with the last-used device automatically.
- If connection fails, delete all the pairing record from your device, and follow the above instructions again.

-4-

Keys and Function

For iOS (iPhone/iPad) and Android devices, you can press "FN" + desired shortcut keys (F1~F12) to use shortcut functions; For windows devices, you can press "Fn"+"Shift"+desired shortcut keys (F1~F12) to use shortcut functions.

Key icon	iOS (iPhone/iPad) (F1~F12 keys)	Android (Smartphone) (F1~F12 keys)	Windows (Smartphone) (F1~F12 keys)	Windows (Smartphone) (F1~F12 keys)
	N/A	N/A	Esc	N/A
	Home	Home	F1	Web browser
	Brightness -	Brightness -	F2	Brightness -
	Brightness +	Brightness +	F3	Brightness +
	Previous track	Previous track	F4	Previous track
	Play/pause	Play/pause	F5	Play/pause
	Next track	Next track	F6	Next track
	Mute	Mute	F7	Mute
	Volume -	Volume -	F8	Volume -
	Volume +	Volume +	F9	Volume +
	Power display	Power display	F10	Power display
	Screen shot	Screen shot	F11	Screen shot
	Lock screen	Lock screen	F12	N/A
	N/A	N/A	N/A	N/A
	N/A	Back	N/A	N/A
	N/A	キーボード表示	N/A	N/A
	戻る	N/A	N/A	N/A
	N/A	N/A	無変換	N/A
	N/A	N/A	変換	N/A
	N/A	N/A	変換	N/A

Holder Stands

Only for holding the smartphones and tablets.

-5-

NOTE: After connected with the device, you must press "Fn" + "A"/"S"/"D" keys (A for iOS, S for Android, D for Windows) to select a corresponding operating system, otherwise some functions are invalid.

For windows 10 device or Android devices, under Japanese input method, Romaji status, you can type these characters by below:

Shift+	#	Shift+	&	Shift+	/
Shift+	(	Shift+	)	Shift+	=
Shift+	^	Shift+	~	Shift+	@
Shift+	+	Shift+	[	Shift+	{
Shift+	]	Shift+	;	Shift+	*

Note: Under Windows 10 system, Japanese input method, Kana, you can type む by pressing and type る by pressing

Holder Stands

Only for holding the smartphones and tablets.

-6-

Switching the Keyboard Language

iOS 8 or below: Cmd + Space  
iOS 9 or above: Ctrl + Space  
Samsung Android: Shift + Space  
Google Android: Ctrl + Space  
Windows: Cmd + Space / Ctrl + Shift

How to Charge it

- Use the included USB cable for charging. Connect one end to a USB charger, and the other to the keyboard. (USB charger is not included)
- In charging, the power indicator will turn red. Generally, it takes approximately 4 hours for a full charge. (Output: DC 5V/500mA)

Important

Set the language of the device to your desired language before use.

- For iOS devices only: Settings > General > Keyboard > Keyboards > Add new keyboard > Select desired language
- For Samsung Android devices only: Settings > Controls > Language and input > Samsung Keyboard > Select input languages > Select desired language
- For Android devices only: Settings > Language & input > Physical Keyboard > Set up keyboard languages > Select desired language
- For Windows devices only: Control Panel > Clock, Language and Region > Select desired language

System Requirements

- iOS 6.0 and above
- Mac OS X v10.6 to Mac OS X v10.12 and above
- Windows XP / Vista / 7 / 8 / 10, PC computer with a Bluetooth host
- Android 3.0 and above with Bluetooth HID profile (Smartphones and Tablets)
- This keyboard is not compatible with Samsung Smart TV (UE37ES5500, UE55KU6400U, UE48JU6400), Mac mini and Nokia phones.

-7-

Power Saving Mode

The keyboard will enter sleep mode after being idle for 30 minutes. To activate it, press any key and wait for 3 seconds.

FAQ

My keyboard fails to connect. If you can't successfully connect the keyboard to your device, please try as following:

- Ensure your Bluetooth function is on.
- Delete all the connection records.
- Turn off the Bluetooth on your devices and turn it again
- Minimize the distance between the IC-BK06lite keyboard and your device as close as possible.
- Fully charge both devices to ensure the pairing process won't be affected by low batteries.
- Restart the keyboard and your devices.

Note: if you connect keyboard by Bluetooth adapter, some adapter may be unable to connect because of compatibility problem.

In Japanese input method, why the punctuation of input and output is different? This keyboard is based on US layout, not Japanese Layout; hence in Japanese input method, the punctuation will be different. When you switch to English(US) input method, the punctuation will be same as layout.

Why some function is not working? Before to use function keys, please read above "Keys and Function" first; in addition, please ensure you have already switched to corresponding system by pressing "Fn" + "A"/"S"/"D" keys (A for iOS, S for Android, D for Windows) switching to iOS/Android/Windows system.

-8-