


超薄型Bluetoothキーボード
 IC-BK13
 取扱説明書

 www.iclever.com


パッケージの内容
 1x Bluetoothキーボード本体
 1x USB 充電ケーブル
 1x 携帯ポーチ
 1x 取扱説明書
 1x 保証カード

仕様

Bluetoothバージョン	Bluetooth 3.0
サイズ	287x133x20mm/11.3x5.24x0.79 in
通信範囲	< 10 m / 32.8 ft
リチウム電池容量	280 mAh
充電時間	< 2 時間
連続使用時間	90 時間
待機時間	90 日
表面材質	ABS
裏面材質	ステンレス・スチール

-1-

インジケータ説明



ペアリング手順

一台目のデバイスのペアリング
 ステップ 1. 電源スイッチをオンにします。電源インジケータが緑色で点灯してから消えます。
 ステップ 2. 「fn+①」を同時に押します。
 ステップ 3. 「fn+②」を押してください。Bluetooth インジケータが緑色で点滅し、デバイスのBluetooth機能をオンにして、使用可能なデバイスを検索します。
 ステップ 4. 「iClever BK13 Maruko」という名のBluetoothキーボードをみつけるとクリックして接続します。
 ステップ 5. 接続された後、Bluetoothインジケータが消灯します。

二台目のデバイスのペアリング
 ステップ 1. 「fn+②」を同時に押します。
 ステップ 2. 「fn+③」を押してください。Bluetooth インジケータが緑色で点滅し、デバイスのBluetooth機能をオンにして、使用可能なデバイスを検索します。
 ステップ 3. 「iClever BK13 Maruko」という名のBluetoothキーボードをみつけるとクリックして接続します。
 ステップ 4. 接続された後、Bluetoothインジケータが消灯します。

三台目のデバイスのペアリング
 ステップ 1. 「fn+③」を同時に押します。
 ステップ 2. 「fn+④」を押してください。Bluetooth インジケータが緑色で点滅し、デバイスのBluetooth機能をオンにして、使用可能なデバイスを検索します。
 ステップ 3. 「iClever BK13 Maruko」という名のBluetoothキーボードをみつけるとクリックして接続します。
 ステップ 4. 接続された後、Bluetoothインジケータが消灯します。

ご注意:
 1. 三台目のデバイスがペアリングされたら、「fn+①」+②「fn+②」+③、「fn+③」+④を押すと、それぞれペアリングされたデバイスに切り替えます。
 2. 再接続機能: キーボードの電源をオンにして、最後に使用したデバイスと自動的に接続します。(接続デバイスのBluetooth機能をオンにしてください)
 3. ペアリングに失敗した場合は、デバイスからペアリング履歴を削除し、上記の手順をもう一度試してみてください。

-2-

ファンクションキー機能

Windowsのタブレットの場合は、「fn」を押しながらをそれぞれのファンクションキーを押してください。

	For Android	For Win	Fn on Windows	For iOS
ESC	N/A	Esc	N/A	N/A
⌂	ホーム	F4	ウェブブラウザ	ホーム
☰	ウィンドウの切り替え	F5	ウィンドウの切り替え	ウィンドウの切り替え
☰	バック	F6	N/A	N/A
⏪	戻る	F7	戻る	戻る
⏸	再生/一時停止	F8	再生/一時停止	再生/一時停止
⏩	先へ	F9	先へ	先へ
🔇	ミュート	F10	ミュート	ミュート
🔊	音量を下げる	F11	音量を下げる	音量を下げる
🔊	音量を上げる	F12	音量を上げる	音量を上げる
Fn+📄	スクリーンショット	スクリーンショット	スクリーンショット	スクリーンショット
Fn+🔄	Bluetooth ペアリング	Bluetooth ペアリング	Bluetooth ペアリング	Bluetooth ペアリング

-4-

キーボードの入力言語の切り替え

Samsung Android: shift + Space
 Google Android: ctrl + Space
 Windows: cmd + Space / ctrl+shift
 iOS 8 とそれ以前のシステム: cmd + Space
 iOS 9 とそれ以降のシステム: ctrl + Space

対応するシステム

- iOS 6.0 とそれ以後のシステム
- Mac OS X v10.6, Mac OS X v10.12 とそれ以後のシステム
- Windows XP / Vista / 7 / 8 / 10 搭載のパソコン (Bluetooth機能が必要)
- Android 3.0 或いはそれ以後のシステム、Bluetooth HID profile機能付きなスマートフォンとタブレット
- このキーボードはSamsung Smart TV (UE37ES5500/UE55KU6400U/UE48JU6400), Mac mini, Nokiaスマホに対応しません。

省エネモード

30分間操作しない場合、キーボードが自動的にスリープモードに入ります。再起動するには、いずれのキーを押して、3秒ほど待ってください。

充電の説明

- 付属されるUSBケーブルを使って充電してください。一端をUBSチャージャーに接続して、もう一端をキーボードに接続してください (USBチャージャーは同梱されていません)。
- 充電中、電源インジケータが赤くなります。フル充電するまで約2時間かかります (出力: DC 5V/500mA)


注意: デバイスとペアリングされた後、fnとOSキー (AndroidにはQ, WindowsにはW, iOSにはE) を押して、オペレーションシステム (OS)を選びます。それなしに、「Fn+Q」-Android 「Fn+W」- Windows 「Fn+E」- iOS

-5-

FAQ (よくある質問)

タブレットと接続できない...

- 電池残量不足が原因ではないかを確認してください。両方のデバイスをフル充電してください。
- お使いのデバイスのBluetooth機能がオンになっているかを確認してください。
- お使いのデバイスとキーボード間の距離が接続可能範囲の10メートル以内かどうか確認してください。


Ultra-slim Universal Wireless Keyboard
 IC-BK13
 User Manual

 www.iclever.com

-6-


Package Contents

1 x Wireless Keyboard
 1 x USB Charging Cable
 1 x Carry Pouch
 1 x User manual
 1 x Warranty Card

Specifications

Bluetooth version	Bluetooth 3.0
Dimensions	287x133x20mm/11.3x5.24x0.79 in
Operating Range	< 10 m / 32.8 ft
Lithium Battery Capacity	280 mAh
Charge time	< 2 hours
Uninterrupted Work Time	90 hours
Stand-by time	90 days
Front side of keyboard	ABS
Back side of keyboard	Stainless steel

Indicator Lights Description



- Caps Lock Indicator:** Press Caps Lock key to switch capital and small letters. Inputting Capital Letters: flash in green color. Inputting Small Letters: automatically turns off.
- Bluetooth Pairing Indicator:** Will flash green after pressing the "fn + pairing" Keys together. It disappears when connected.
- Power Switch:** Lights up green for about 3s when being turned on.
- Battery Indicator:** Red light will turn on when the keyboard is charging and turns off once fully charged.
- Micro Charging Port:** Only for charging.
- Keyboard Switch Button.**

-7-

Pairing Steps

Pairing with the 1st device
 Step 1. On the keyboard, slide the power button on. The green light will be on for 3s and then turn off.
 Step 2. Press "fn + ①".
 Step 3. Press "fn + pairing", Bluetooth indicator flash green, starting to search the available bluetooth device.
 Step 4. Find the Bluetooth name "iClever BK13 Maruko" and click for connection.
 Step 5. The Bluetooth indicator will be OFF after successfully paired.

Pairing with the 2nd device
 Step 1. Press "fn + ②".
 Step 2. Press "fn + pairing", Bluetooth indicator flash green, starting to search the available bluetooth device.
 Step 3. Find the Bluetooth name "iClever BK13 Maruko" and click for connection.
 Step 4. The Bluetooth indicator will be OFF after successfully paired.

Pairing with the 3rd device
 Step 1. Press "fn + ③".
 Step 2. Press "fn + pairing", Bluetooth indicator flash green, starting to search the available bluetooth device.
 Step 3. Find the Bluetooth name "iClever BK13 Maruko" and click for connection.
 Step 4. The Bluetooth indicator will be OFF after successfully paired.

NOTE:
 1. Three devices can be actively paired at one time, only need to press "fn + ① ② ③" key, changing to the accorded paired device.
 2. Re-connection function: Turn on the keyboard, it can connect with the last used device automatically.
 3. If connection is failure, delete the pairing record from your device, and try the above procedures again.

-9-

Keys and Function

For the Windows tablets, press and hold the "Fn" keys while pressing the function keys.

	For Android	For Win	Fn on Windows	For iOS
ESC	N/A	Esc	N/A	N/A
⌂	Home	F4	Web browser	Home
☰	Switch windows	F5	Switch windows	Switch windows
⏪	Back	F6	N/A	N/A
⏪	Previous track	F7	Previous track	Previous track
⏸	Play/pause	F8	Play/pause	Play/pause
⏩	Next track	F9	Next track	Next track
🔇	Mute	F10	Mute	Mute
🔊	Volume -	F11	Volume -	Volume -
🔊	Volume +	F12	Volume +	Volume +
Fn+📄	Screen shot	Screen shot	Screen shot	Screen shot
Fn+🔄	Bluetooth Pairing	Bluetooth Pairing	Bluetooth Pairing	Bluetooth Pairing

NOTE: After connecting with the device, you must press Fn + relative OS key (Q for Android, W for Windows, E for iOS) to select operating system, otherwise some key's function are invalid.

-10-

How to switch keyboard language

Samsung Android: shift + Space
 Google Android: ctrl + Space
 Windows: cmd + Space / ctrl+shift
 iOS 8 or below: cmd + Space
 iOS 9 or above: ctrl + Space

System requirements

- iOS 6.0 and above
- Mac OS X v10.6 to Mac OS X v10.12 and above
- Windows XP / Vista / 7 / 8 / 10, PC computer with a Bluetooth host
- Android 3.0 and above with Bluetooth HID profile (Smartphones and Tablets)
- This keyboard is not compatible with Samsung Smart TV (UE37ES5500, UE55KU6400U, UE48JU6400), Mac mini and Nokia phones.

Power Saving Mode

The keyboard will enter sleep mode after being idle for 30 minutes. To activate it, press any key and wait for 3 seconds.

How to Charge it

- Use the included USB cable for charging. Connect one end to a USB charger, and the other to the keyboard. (USB charger is not included)
- In charging, the power indicator will turn red. Generally, it takes approximately 2 hours for a full charge. (Output: DC 5V/500mA)

-11-

FAQ

If you are unable to connect the keyboard to your tablet, please try the following:

- Starting with a full charge on both devices ensures that process won't be interrupted by a low battery.
- Check your tablet's Bluetooth is on.
- Make sure that the keyboard is within the effective operation distance of 32.8 feet (10m).

-12-