

iclever

バックライト付き折りたたみ式 Bluetoothキーボード
IC-BK05 / IC-BK20

取扱説明書

www.iclever.com

パッケージ内容

1 x iclever IC-BK20 Bluetoothキーボード
1 x Micro USBケーブル
1 x キャリーポーチ
1 x 取扱説明書
1 x 保証カード

インジケータ

①電源インジケータ ②状態インジケータ ③キャップロックインジケータ

①電源インジケータ:
1)キーボードを開くと、電源が自動的にオンになります。電源インジケータが緑色で5秒くらい点灯し、そして消灯します。
2)電量不足: 電量不足の場合、電源インジケータが赤色で点滅します。キーボードを充電してください。
3)充電中: 赤色で点灯します。充電完了: 自動的に消灯します。
4)バッテリー残量表示: 「Fn + 🔋」キーを押すと、緑色で点滅します。(一回点滅: 残量約25%; 二回点滅: 残量約50%; 三回点滅: 残量約75%; 四回点滅: 100%電量)
②状態インジケータ
Fn と numlock キーを押すと、お使いのBluetooth対応デバイスとペアリングすることができます。

-1-

ペアリングモード: インジケータが青色で点滅します。ペアリング完了: 自動的に消灯します。
③キャップロックインジケータ:
キャップロックキーを押すと、大文字・小文字を切り替えることができます。
大文字を入力する際: インジケータが緑色で点滅します。
小文字を入力する際: 消灯
Androidシステムの場合、インジケータが点灯しないこともあります

製品特徴

1. Bluetooth ワイヤレス接続とUSB 有線接続の二つの接続方法があります

2. USB 有線接続された状態でも「Fn + 🔌」や「Fn + 🖱」を押せば Bluetooth ワイヤレス接続に切り替えることができます。

-2-

3. 真ん中の二つ黒いスタンドを下に倒せば、タイプ中のキーボードのバランスを保つことができます。

操作ガイド

バックライト機能
「Fn + ✨」キーを押すと、バックライト機能がオン/オフになります。「Fn + ✨」キーを一回押すと、バックライト機能がオンになります。「Fn + ✨」キーを二回押すと、バックライトがより明るくなります。「Fn + ✨」キーを三回押すと、バックライト機能がオフになります。「Fn + ✨ + ▲」或いは「Fn + ✨ + ▼」キーを押すと、バックライトの色を変えることができます。

接続
a. Bluetooth ワイヤレス接続
1. キーボードを開いて電源をオンにしてください。
2. 「Fn + 🔌」を押してください。
3. 「Fn + Pairing」キーを押して状態インジケータが青色で点滅し、ペアリングモードに入ります。
4. お使いのデバイスのBluetooth機能を有効にし、接続可能なデバイスを探します。「iclever IC-BK20キーボード」が表示されると、クリックして接続します。
5. 接続完了後、「Fn+Q/W/E」を押して操作システムを選択してください
(Android: Fn+Q; Windows: Fn+W; iOS: Fn+E)
ご注意:
1. ペアリング完了後、状態インジケータが自動的に消灯します。
2. ペアリングが失敗する場合、上記の接続手順に従って、再試行してください。

-3-

b. USB 有線接続
1. キーボードを開いて電源をオンにしてください。
2. キーボードを付属されたUSBケーブルと接続し、もう一端をデバイスと接続してください。
3. 「Fn + 🖱」キーを押して、USB有線接続機能が有効になります。
4. 接続完了後、「Fn+Q/W/E」を押して操作システムを選択してください

ファンクションキ

キー	Android	Windows	iOS
⌘	N/A	Esc	N/A
⌘	ホーム	ウェブブラウザ	ホーム
* ⌘	N/A	N/A	Brightness down
* ⌘	N/A	N/A	Brightness up
🔍	検索	検索	検索
⏪	曲戻し	曲戻し	曲戻し
⏸	再生/一時停止	再生/一時停止	再生/一時停止
⏩	曲送り	曲送り	曲送り
⏹	ミュート	ミュート	ミュート
🔊	ボリューム-	ボリューム-	ボリューム-
🔊	ボリューム+	ボリューム+	ボリューム+
📸	Screenshot	Screenshot	Screenshot
🔒	ロック	ロック	ロック
Fn + ⌘	N/A	N/A	キーボード表示
Fn + 🔍	戻る	N/A	N/A
Fn + 🔋	バッテリー残量確認	バッテリー残量確認	バッテリー残量確認
Fn + 🔌	Bluetooth ペアリング	Bluetooth ペアリング	Bluetooth ペアリング

-4-

タブレットに接続した場合、日本語状態で以下の文字はどのように打てますか?

押すキー	文字	押すキー	文字	押すキー	文字
Shift+ 🔠	"	Shift+ 🔡	&	Shift+ 🔢	、
Shift+ 🔣	(Shift+ 🔤)	Shift+ 🔥	=
Shift+ 🔦	^	Shift+ 🔧	~	Shift+ 🔨	@
Shift+ 🔩	、	Shift+ 🔪	[Shift+ 🔫	{
Shift+ 🔬	;	Shift+ 🔭]	Shift+ 🔮	}
Shift+ 🔯	:	Shift+ 🔰	*		

入力言語の切り替え
iOS 8或いはそれ以前のシステム: Win + Space
iOS 9或いはそれ以後のシステム: Ctrl + Space
Samsung Androidシステム: Shift + Space
Google Androidシステム: Ctrl + Space
Windowsシステム: Win + Space

重要事項—入力言語の設定
本製品は多国言語対応であるため、使用する前にご利用したい入力言語に設定してください。
1. iOSデバイスの場合
設定>一般>キーボード>キーボード>新しいキーボードを追加>使いたい言語を選択
2. Samsung Androidデバイスの場合
設定>コントロール>言語と文字入力>Samsungキーボード>入力言語を選択>使いたい言語を選択

-5-

3. Androidデバイスの場合
設定>言語と文字入力>物理キーボード>キーボードレイアウト設定>使いたい言語を選択
4. Windowsデバイスの場合
コントロールパネル>時間・言語・地域>使いたい言語を選択

対応するシステム

端末	システム	対応状況
iPad / iPhones全機種	iOS 6.0 以後のシステム	○
パソコンやノートパソコン	Windows XP / Vista / 7 / 8 / 10 (Bluetooth機能あり)	○
Mac / Macbooks	Mac OS X v10.6 ~ Mac OS X v10.12或いはそれ以後のシステム	○
スマートフォンやタブレット	Android 3.0或いはそれ以後のシステム (Bluetooth機能あり)	○
Samsung Smart TV (品番UE37ES5500, UE55K, UE6000, UE6800, UE7000, Mac mini & Nokia)	-	×

省エネモード
30分間操作しない場合、キーボードが自動的にスリープモードに入ります。再起動するには、いずれのキーを押して、3秒くらい待つてください

-6-

充電について

1. 充電する場合はキーボードを付属されたUSBケーブルと接続し、もう一端をUSBチャージャーに接続してください。(USBチャージャーが同梱されていません)
2. 充電中電源インジケータが赤色で点灯します。フル充電するまで約4時間が必要です。(出力電圧: DC 5V/500mA)

よくある質問

デバイスと接続できない...
1. お使いのデバイスとキーボードのバッテリー残量が不足ではないかを確認してください。
2. お使いのデバイスのBluetooth機能がオンになっていますかを確認してください。
3. お使いのデバイスとキーボードの距離を10メートル以内にしてください

-7-

iclever

Tri-folding Wireless Keyboard with backlit
IC-BK05 / IC-BK20

User Manual

www.iclever.com

Package Contents

1 x Wireless Keyboard
1 x Micro USB Cable
1 x Carry Pouch
1 x User Manual
1 x Warranty Card

Indicator Lights Description

Power Indicator Status Indicator Caps Lock Indicator

① Power Indicator:
1) Unfold the keyboard: It will light in green color for several seconds and then turns off.
2) Low battery capacity: When the keyboard is in low battery capacity, it will flash in red color to remind you to charge it.
3) Charging: stably on in red color.
Fully Charged: automatically turns off.
4) Battery capacity display: Press "Fn + 🔋" keys, it flashes in green color. Every flash represents 25% battery power (in total 4 times flashes, 100% remaining battery power).

-8-

② Status Indicator
Press "Fn + 🔌" keys to pair the keyboard with your Bluetooth-enabled devices.
Pairing: quick flash in blue color
Successfully Paired: automatically turns off
③ Caps Lock Indicator
Press Caps Lock key to switch capital and small letters.
Inputting Capital Letters: lit in blue color
Inputting Small Letters: automatically turns off
(For Android users, the Caps Lock indicator may not appear, but the Caps Lock function is still activated as per normal.)

Feature

1. Two working conditions: Bluetooth wireless connection and USB wired connection

2. After connecting to the USB port, you can freely switch between BT connection and wired connection by pressing "Fn + 🔌" or "Fn + 🖱". That is to say, one of them is in activated status while the other is in standby status.

-9-

3. With two foot stands on both side to keep balance and stable when typing.

Backlit Function

Press "Fn + ✨" key to turn on/off backlit function
1st time press to turn on backlit
2nd time press to increase backlit brightness
3rd time press to turn off backlit.
Press "Fn + ✨ + ▲" key or "Fn + ✨ + ▼" key to change backlit colors.

Operation Instruction

a. Bluetooth Wireless Connection
Step 1. Unfold the keyboard to power on it.
Step 2. Press "Fn + 🔌" keys to enjoy wireless technology lifestyle.
Step 3. Press "Fn + Pairing" keys, the Status Indicator will flash in blue color to enter pairing mode.
Step 4. Activate the Bluetooth function of your device and search other Bluetooth devices. Find the keyboard name (iclever IC-BK20 Keyboard) and click to connect them.

Note:
1. The Status Indicator will automatically turn off if they are successfully paired.
2. If the pairing process is failed, please retry the above steps until successful pairing.
3. Only one device can be actively paired at one time.
4. For some desktop computers, you may need a Bluetooth dongle to help Bluetooth pairing process. (Bluetooth dongle is not included.)

-10-

b. USB Wired Connection
Step 1. Unfold the keyboard to power on it.
Step 2. Plug the provided Micro USB cable into this keyboard and connect the other end to your device.
Step 3. Press "Fn + 🖱" keys to successfully connect them, then you can enjoy your wired technology lifestyle.

Keys and Function

Key icon	Android	Windows	iOS
⌘	N/A	Esc	N/A
⌘	Home	Web browser	Home
* ⌘	N/A	N/A	Brightness down
* ⌘	N/A	N/A	Brightness up
🔍	Search for	Search for	Search for
⏪	Previous track	Previous track	Previous track
⏸	Play/Pause	Play/Pause	Play/Pause
⏩	Next track	Next track	Next track
🔇	Mute	Mute	Mute
🔊	Volume -	Volume -	Volume -
🔊	Volume +	Volume +	Volume +
📸	Screenshot	Screenshot	Screenshot
🔒	Lock	N/A	Lock
Fn + ⌘	N/A	N/A	Keyboard display
Fn + 🔍	Back	N/A	N/A
Fn + 🔋	Remaining power capacity	Remaining power capacity	Remaining power capacity
Fn + 🔌	Bluetooth pairing	Bluetooth pairing	Bluetooth pairing

-11-

NOTE: After connecting with the device, you must press Fn + relative OS key (A for Android, S for Windows, D for iOS) to select operating system, otherwise some key's function are invalid.

For the windows tablets, how to type the below letters in the status of Japanese.

押すキー	文字	押すキー	文字	押すキー	文字
Shift+ 🔠	"	Shift+ 🔡	&	Shift+ 🔢	、
Shift+ 🔣	(Shift+ 🔤)	Shift+ 🔥	=
Shift+ 🔦	^	Shift+ 🔧	~	Shift+ 🔨	@
Shift+ 🔩	、	Shift+ 🔪	[Shift+ 🔫	{
Shift+ 🔬	;	Shift+ 🔭]	Shift+ 🔮	}
Shift+ 🔯	:	Shift+ 🔰	*		

Switching the keyboard's language
iOS 8 or below: Win + Space
iOS 9 or above: Ctrl + Space
Samsung Android: Shift + Space
Google Android: Ctrl + Space
Windows: Win + Space

-12-

IMPORTANT

Set the language of the device to your desired language before use.
1. For iOS devices only:
Settings > General > Keyboard > Keyboards > Add new keyboard > Select desired language
3. For Android devices only:
Settings > Controls > Language and input > Samsung Keyboard > Select input languages > Select desired language
3. For Windows devices only:
Settings > Language & input > Physical Keyboard > Set up keyboard layouts > Select desired language
4. For Windows devices only:
Control Panel > Clock, Language and Region > Select desired language

System requirements

- iOS 6.0 and above
- Mac OS X v10.6 to Mac OS X v10.12 and above
- Windows XP / Vista / 7 / 8 / 10 , PC computer with a Bluetooth host
- Android 3.0 and above with Bluetooth HID profile (Smartphones and Tablets)
- This keyboard is not compatible with Samsung Smart TV (UE37ES5500, UE55K, UE6000, UE6800, UE7000, Mac mini and Nokia phones).

Power Saving Mode
The keyboard will enter sleep mode after being idle for 30 minutes. To activate it, press any key and wait for 3 seconds.

-13-

How to Charge it

1. Use the included USB cable for charging. Connect one end to a USB charger, and the other to the keyboard. (USB charger is not included)
2. In charging, the power indicator will turn red. Generally, it takes approximately 4 hours for a full charge. (Output: DC 5V/500mA)

FAQ

If you are unable to connect the keyboard to your tablet, please try the following:
1. Starting with a full charge on both devices ensures that process won't be interrupted by a low battery.
2. Check your tablet's Bluetooth is on.
3. Make sure that the keyboard is within the effective operation distance of 33 feet (10 m).

-14-